

## Digital Frontier DFA-5300Voice/DFA5300GSM 16 Zone Alarm System

### Keypad Command Summary

Arm/Disarm Alarm	User Password or Master Password (Without Partition) Master Password 1 (To Arm/Disarm Partition 1) Master Password 2 (To Arm/Disarm Partition 2) Master Password 0 (To Arm/Disarm Both Partition)
Home Arming	<b>H</b> (hold 3 sec to on Both Partition)
Away Arming	<b>A</b> (hold 3 sec to on Both Partition)
Bypass	* <b>4</b> (Master password) (Zones to Bypass) #
Display Memory	* <b>5</b> (Any Key to End)
Display Trouble	* <b>50</b> (Any Key to End) 1: AC Fail 2: Battery Low 3: CMS Fail 4: GSM Fail 7: Time Clock Failed
Add/Modify Password	* <b>6</b> (Master Password) <b>n</b> (New Password repeat 2 times) Value of n: 0=Master Password 1 to 8=User Password 1 to 8
Delete Password	* <b>6</b> (Master Password) <b>n</b> *
Change Reporting Phone Number	* <b>7</b> (Master Password) ( <b>1 or 2 or 3 or 4</b> ) (Phone Number) #
Door Chime	* <b>81</b> (Zones) #
Walk Test	* <b>82</b> (Zones) #
Manual Testing CMS	* <b>83</b>
Control Device 1 or 2 or 3 or 4	* <b>91</b> (On/Off) or * <b>92</b> (On/Off) or * <b>93</b> (On/Off) or * <b>94</b> (On/Off)
Control Device (All On)	* <b>95</b>
Control Device (All Off)	* <b>96</b>
Back to Ready	#

### DFA-5300Voice/DFA5300GSM 16 Zone

### Smart Dialer Operation Summary

Key	Status
1	Disarmed System
2	Armed System
3	Home Automation; Individual On/Off (1 to 4) # ; All On (5) # ; All Off (6) #
4	Bypass Zone (1 to 8) #
5	Memory Mode
6	Panic Button
#	To Exit

## Extra Features for Using PGM Output

### Steps To Enter Programming:

#### \* 1 (Master Password) (Location) (HHMM)

Location	Description	Default Value
30	Current Time 24 hours format HHMM	-
31	Auto Arm Time for Partition 1.24 hours format HHMM	9999
32	Auto Disarm Time for Partition 1.24 hours format HHMM	9999
33	Auto Arm Time for Partition 2.24 hours format HHMM	9999
34	Auto Disarm for Partition 2.24 hours format HHMM	9999
35	Night Mode begins time. 24 hours format HHMM	9999
36	Night Mode begins time. 24 hours format HHMM	9999
37	PGM On Time 1.24 hours format HHMM	9999
38	PGM Off Time 1.24 hours format HHMM	9999
39	PGM On Time 2.24 hours format HHMM	9999
40	PGM Off Time 2.24 hours format HHMM	9999
41	PGM Auto Off Timer. From 1 to 255	005