

EzeProx Proximity, Default=0000, Output 1 = Locks

Change Master Code; [Master Code][#00#][New Code][#]

User Code; [Master Code][#User#][New Code][#][User Status]

[User Status]:

1. Operate Output 1 **

2. Operate Output 2

3. Operate Output 1 and 2

4. Operate Output 1 or 2

5. 'Nite Lock' Output 1

6. 'Nite Lock' Output 2

7. 'Nite Lock' Output 1 or 2

Add Card: [Master Code][#96#] flash Card [User#][#][Output#][#]

Add Cards: [Master Code][#90#][Start Card ID][#][End Card ID][#][Output#][#]
flash all cards once.

Delete Card; 1. [Master Code][#93#]flash card or

2. [Master Code][#94#][Card ID][#][Card ID][#]

Delete User Code; 1. [Master Code][#91#][User Code] or

2. [Master Code][#92#][User#]

Output Operation; [Master Code][#99#][Output#][Output Control#]

Output Control# 1 - 0.5 sec, 2 - 1 sec, 3 - 2 sec, 4 - 4 sec,

5 - 8 sec, 6 - 16 sec, 7 - 32 sec, 8 - latch

Operational:

Operate Output; [access code][#]

