

Digital Frontier DFA-3300/3400 8 Zone Alarm System

Keypad Command Summary

Arm/Disarm Alarm	User Password or Master Password (Without Partition) Master Password 1 (To Arm/Disarm Partition 1) Master Password 2 (To Arm/Disarm Partition 2) Master Password 0 (To Arm/Disarm Both Partition)
Home Arming	H (hold 3 sec to on Both Partition)
Away Arming	A (hold 3 sec to on Both Partition)
Bypass	* 4 (Master password) (Zones to Bypass) #
Display Memory	* 5 (Any Key to End)
Display Trouble	* 50 (Any Key to End) 1: AC Fail 2: Battery Low 3: CMS Fail 5: Supervision: Press 5 to check zones 6: Transmitter's Battery Low, Press 6 to check zones
Add/Modify Password	* 6 (Master Password) n (New Password repeat 2 times) Value of n: 0=Master Password 1 to 8=User Password 1 to 8
Delete Password	* 6 (Master Password) n *(New Password repeat 2 times)
Change Reporting Phone Number	* 7 (Master Password) (1 or 2 or 3 or 4) (Phone Number) #
Door Chime	* 81 (Zones) #
Walk Test	* 82 (Zones) #
Manual Testing CMS	* 83
Control Device 1	* 9 (4 off or 5 on 6 Status)
Control Device 2	* 9 (7 off or 8 on 9 Status)
Back to Ready	#

DFA3300/3400 Smart Dialer Summary

Key	Status
1	Disarmed System
2	Armed System
3	Check Alarm Armed/Disarmed
4	Off PGM 1
5	On PGM 1
6	Check PGM 1 On/Off
7	Off PGM 2
8	On PGM 2
9	Check PGM 2 On/Off
0	Zone Reporting

Note: Please key in the Master Password before you key-in the above command key.
One Beep Tone is Off ; Two Beep Tone is On

Extra Features for Using PGM Output

Steps To Enter Programming:

* 1 (Master Password) (Location) (HHMM)

Location	Description	Default Value
30	Current Time 24 hours format HHMM	-
31	Auto Arm Time for Partition 1.24 hours format HHMM	9999
32	Auto Disarm Time for Partition 1.24 hours format HHMM	9999
33	Auto Arm Time for Partition 2.24 hours format HHMM	9999
34	Auto Disarm for Partition 2.24 hours format HHMM	9999
35	Night Mode begins time. 24 hours format HHMM	9999
36	Night Mode begins time. 24 hours format HHMM	9999
37	PGM On Time 1.24 hours format HHMM	9999
38	PGM Off Time 1.24 hours format HHMM	9999
39	PGM On Time 2.24 hours format HHMM	9999
40	PGM Off Time 2.24 hours format HHMM	9999
41	PGM Auto Off Timer. From 1 to 255	005