

RAN-GER[®] ALARM

VOICE INTRUSION SYSTEM

The RAN-GER[®] RC-9V is an advanced 9 zones wire control panel for residential and light commercial intrusion alarms. Advanced on - board features included automation with event scheduler and combining a wide range of features with easy operation.



Main Features

- 9 monitoring with programmable zones.
- Pulse delay zone available.
- Support up to 4 LED keypads with a maximum distance of up to 150m.
- 4 private telephones with event report filtering.
- Remote telephones voice guided sessions for status messages, alerts and control options.
- Telephones voice or tones optional interactive menu.
- 2 Central Monitoring System (CMS) numbers and 1 CMS account ID.
- 4 flexible PGM automation features
- Multi-level lightning protection.
- Smoke reset power supply (PGM) on OFF Siren.
- Very easy to operate and configure.

Product Specifications

Electrical Characteristics

• DC Input Power supply	AC 16-24V, 50Hz, 3A
• Current consumption	100mA
• Keypad current consumption	100mA
• Backup battery type	12V, 7AH
• Battery cut-off voltage	10.5V
• Battery charging current	600mA

Operation Characteristics

• Zones	9
• Zones types	Entrance, Internal Delay, Internal, Burglary, 24-hour, Fire and Silent and Force arming.
• Zone connection	NC, NO and EOL
• Keypad Support numbers	Up to 4 LED keypad with a maximum distance of up to 150m.
• 3 quick emergency keys	Fire, Medical, and Panic.
• Arming mode	Home mode and Stay mode Support 1-key fast arming
• PGM Output Numbers	4
• Siren, Aux and PGM output power	12V
• Siren, Aux and PGM output current	2.5A
• Remote telephone guided type	Support Voice or Tone. Support remote arm/disarm, bypass zone, Check status and remote ON/OFF PGM
• CMS Telephone dial out support	Support 2 CMS phone numbers and 1 account ID Support Ademco Contact ID format
• Reporting telephone numbers	4
• Access code	1 Master code, 8 User codes (The 8th User access code used as duress code)

5 Channel Protection

Burglary

A window is forced open in the middle of the night



Threat of Fire

A fire breaks out while you are sleeping



Police Emergency

An intruder is lurking around your premises



Medical Emergency

When medical help is required



Duress

When you are forced to disarm the system